

Estate Swing 24V E-S Classic board - Estate Swing 433 MHz 2 Channel receiver (433ESREC)

Gate Opener Terminal Name	Corresponding Accessory Terminal or Wire
PUSH1	2nd terminal from the left labeled CH1
COM	3rd terminal from the left labeled CH1
GND	7th terminal from the left labeled GND
V +	6th terminal from the left labeled V+

Installation Notes:

- use 18 - 22 gauge wire to make connections - not included.
- VERY IMPORTANT - if your receiver has a short piece of wire connecting CH1 to GND - REMOVE this wire.
- The receiver is drip proof - as long as it is mounted upright water will not enter it because of the contours of the case.

